

❖ CM-040 MCL / CB-040 MCL Progressive Scan

C₃ Camera Suite
Unlimited
Digital
Switchability



- *Compact series 1/2" progressive scan camera*
- *Monochrome and Bayer mosaic color versions*
- *776 (h) x 582 (v) active pixels*
- *8.3 μ m square pixels*
- *61.15 frames/second with full resolution in continuous operation*
- *60 frames/second with external trigger and full resolution*
- *Up to 280 frames/second with partial scan*
- *111 frames/second with vertical binning (CM-040 MCL only)*
- *Shutter speed from 27.437 μ s to 2 sec. using Pulse Width Control*
- *Programmable exposure from 54.874 μ s to 16.553 ms*
- *Pre-select and Pulse width trigger modes*
- *LVAL-synchronous/-asynchronous operation (auto-detect)*
- *Auto iris lens video output to support dynamic lighting conditions*
- *10 or 8-bit output*
- *Setup by Windows NT/2000/XP via serial communication*
- *Right angle adapter (optional)*

**CAMERA
Link**
(Mini Camera Link)




Specifications for CM-040 MCL / CB-040 MCL

Specifications	CM-040 MCL / CB-040 MCL
Sensor	1/2" progressive scan CCD
Pixel Clock	33.75 MHz
Frame rate full frame	61.15 frames/second (596 lines per frame)
Active area	6.49 (h) x 4.83 (v) mm
Cell size	8.3 x 8.3 μm
Active pixels	776 (h) x 582 (v)
Color (CB-040 MCL)	Raw Bayer output, host-based interpolation
Read-out modes	Full 776 (h) x 582 (v) 61 fps 2/3 partial scan 776 (h) x 390(v) 87 fps 1/2 partial scan 776 (h) x 294 (v) 110 fps 1/4 partial scan 776 (h) x 146 (v) 186 fps 1/8 partial scan 776 (h) x 74 (v) 280 fps Vertical binning 776 (h) x 291 (v) 111 fps* *NOTE: CM-040 MCL only
Sensitivity (CM-040 MCL)	0.2 Lux (On sensor, Max. gain, shutter off, 50% video)
Sensitivity (CB-040 MCL)	1.3 Lux (On sensor, Max. gain, shutter off, 50% video)
S/N ratio	>50dB (0 dB gain)
Video output	8 or 10 bit in Mini-CL
Auto-iris lens video	0.7 Vp-p
Gain	Manual, -3dB to +24dB
Synchronization	Int. X-tal or ext. trigger
Inputs	Camera Link TTL Ext. trigger, LVDS (CC 1) Ext. trigger 4V ±2V
Outputs	Camera Link TTL Clk., FVAL, LVAL, Data, EEN XEEN
Trigger modes	Pre-select, Pulse Width
Electronic shutter	1/60 to 1/10,000 in 10 steps
Pre-set shutter	2L (54.87μs) to 596L (16.353ms) in 1L steps
Programmable exposure	27.437μs to 2 sec.
Pulse Width Control	
Accumulation	Auto-detect LVAL-synchr. / asynchr.
Control interface	Mini-CL serial communication
Functions controlled by serial communication	Shutter, Trigger mode, Readout mode, Trigger Polarity, Black level, Gain,
Indicators on rear panel	LED for power and trigger input
Operating Temperature	-5°C to +45°C
Humidity (operation)	20 - 90% non-condensing
Storage temp./humidity	-25°C to +60°C / 20 to 90%
Vibration	10G (20Hz to 200 Hz XYZ)
Shock	70G
Regulations	CE (EN 61000-6-2, EN-61000-6-3), FCC part 15 class B, RoHS/WEEE
Power	12V DC ±10% 3 W
Lens mount	C-mount
Dimensions (H x W x L)	29 x 44 x 66 mm (CM/CB-040 MCL) 29 x 44 x 93.5 mm (CM/CB-040 MCL-RA)
Weight	115 g (CM/CB-040 MCL) 155 g (CM/CB-040 MCL-RA)

Ordering Information


CM-040 MCL	1/2" Monochrome Progressive Scan Camera
CB-040 MCL	1/2" Bayer Mosaic Color Progressive Scan Camera
CM-040 MCL-RA	1/2" Monochrome Progressive Scan Camera with Right angle adapter
CB-040 MCL-RA	1/2" Bayer Mosaic Color Progressive Scan Camera with Right angle adapter
Option:	1/2" Bayer Mosaic Color Progressive Scan Camera – Glassless
CM-040 MCL-GL	

Connector pin-out



HIROSE HR10A-10R-12PB-01





Pin	Signal
1	Ground
2	+12V DC
3	Ground
4	Auto Iris lens video output
5	Ground
6	N/C
7	N/C
8	Ground
9	XEEN out
10	Trigger in*
11	+12V DC
12	Ground




Pin	Signal	Function
1	14	GND
2	15	-/+ Tx0
3	16	-/+ Tx1
4	17	-/+ Tx2
5	18	-/+ Txclk
6	19	-/+ Tx3
7	20	+/-SerTC
8	21	-/+ SerTFG
9	22	CC1-/CC1+
10	23	CC2-/CC2+
11	24	CC3-/CC3+
12	25	CC4-/CC4+
13	26	GND

*) in Mini-CL or 12-pin Hirose


Dimensions



Spectral Response CM-040 MCL



Spectral Response CB-040 MCL



FVAL auto-detect trigger function (next LVAL or immediate)



- (1) Within this period camera starts accumulation at next LVAL (prevents feed-through noise)
- (2) Avoid trigger at FVAL transition, as function may randomly switch between "next LVAL" and "immediate"
- (3) Within this period camera starts accumulation immediately (no delay)

Europe, Middle East & Africa
 Phone +45 4457 8888
 Fax +45 4491 3252

Asia Pacific
 Phone +81 45 440 0154
 Fax +81 45 440 0166

Americas
 Phone (Toll-Free) 1 800 445 5444
 Phone +1 408 383 0300



Visit our web site on www.jai.com See the possibilities

Company and product names mentioned in this datasheet are trademarks or registered trademarks of their respective owners. IAI AS cannot be held responsible for any technical or typographical errors and reserves the right to make changes to products and documentation without prior notification.